

Link do produktu: <https://matjul.pl/konwerter-econ-basic-single-lnb-e-100-p-4038.html>



Konwerter Econ Basic Single LNB E-100

Cena	29,00 zł
------	-----------------

Dostępność	Dostępny
------------	-----------------

Czas wysyłki	24 godziny
--------------	-------------------

Numer katalogowy	LNB E-100
------------------	------------------

Kod producenta	LNB E-100
----------------	------------------

Opis produktu

Konwerter Econ Basic Single LNB E-100



Specyfikacja:

- Legacy Outputs: 1
- Noise Figure: 0.1dB
- Reflector Type: Offset
- Clamp size: 40mm
- Input Frequency Range: 10.7GHz - 11.7 GHz (Low Band)
- Input Frequency Range: 11.7GHz - 12.7 GHz (High Band)
- Output Frequency Range: 950 MHz - 1950MHz (Low Band)
- Output Frequency Range: 1100 MHz - 2150 MHz (High Band)
- L.O. Frequency: 9.75 GHz (Low Band) / 10.6GHz (High Band)
- L.O. Frequency Phase Noise: -60dBc/Hz @ 1KHz (Max) / -85dBc/Hz @10KHz (Max) / -95dBc @ 100KHz (Max)
- Conversion Gain: 58-63dB
- Gain Flatness 26MHz Bandwidth: +/-0.5dB/36MHz
- Polarity Switching Voltage: Horizontal: 16-18V / Vertical: 12-14.5V
- High Band Switching: 22KHz +/- 4KHz
- Cross Pol. Isolation: >=18dB (Typ.)
- Image Rejection: 40dB (Min)
- Output Spurious:
- Power Consumption: 80mA (Typ.)
- Output Connector Type: 75Ohm - F Type (Female)



Matjul
Krzysztof Żarczyński
Grodziszczce 75A
58-100 Świdnica

-
- Operating Temperature Range: -40°C - +65°C



